

國立中央大學97學年度碩士班考試入學試題卷

所別：電機工程學系碩士班 電子組

科目：計算機概論 共 3 頁 第 1 頁

*請在試卷答案卷(卡)內作答

I. [6pt] Please discuss the difference between local variables, global variables, and static variables in C/C++ language.

II. [5pt] Identify and correct the errors of the following code:

```
class Q {
public:
    int Q(int);
    void setQ(int);
    void printQ();
    int operateQ(int);
private:
    int qData;
} // end class Q
```

參考用

III. What are the execution results of the following C/C++ program segments ?

<p>(1) [5pt]</p> <pre>int a; double result; for (a = 1; a <= 10; a++) { result = (a + 2) / a; printf("(%d + 1) / %d = ", a, a); printf("%f\n", result); }</pre>	<p>(2) [5pt]</p> <pre>int i; char command[] = "%7s\n"; char star[] = "*****"; for (i = 7; i > 0; i--2) { star[i] = 0; printf(command, star); *(command+1) --= 1; }</pre>
<p>(3) [6pt]</p> <pre>#include <stdio.h> void f1 (int *); void f2 (int); void f3 (int &); int main () { int b = 2; printf("Initially, b = %d\n", b); f1(&b); printf("After f1, b = %d\n", b); f2(b); printf("After f2, b = %d\n", b); f3(b); printf("After f3, b = %d\n", b); return 0; }</pre>	<pre>void f1 (int *b) { (*b) *= 2; printf("During f1, b = %d\n", *b); } void f2 (int b) { b *= 3; printf("During f2, b = %d\n", b); } void f3 (int &b) { b *= 4; printf("During f3, b = %d\n", b); }</pre>
<p>(4) [8pt]</p> <pre>#include <stdio.h> int print_series (int); int main () { print_series(3); return 0; }</pre>	<pre>int print_series (int x) { int sum; printf("f(%d) = ", x); if (x > 1) { printf("f(%d) + f(%d)\n", x-1, x-2); sum = print_series (x-1) + print_series (x-2); printf("So, f(%d) = %d\n", x, sum); } else { sum = 1; printf("%d\n", sum); } return sum; }</pre>

國考

注意：背面有試題

國立中央大學97學年度碩士班考試入學試題卷

所別：電機工程學系碩士班 電子組

科目：計算機概論 共 3 頁 第 2 頁

*請在試卷答案卷(卡)內作答

參考用

<p>(5) [5pt]</p> <pre>int x; for (x = 30; x >= 0; x--) { if (x%4 == 0) continue; if (x%17 == 16) break; cout << x << " "; } cout << endl << "The final value of x is: " << x << endl;</pre>	<p>(6) [5pt]</p> <pre>int number1 = 5; //number1 = 00000000 00000101 int number2 = 12; //number2 = 00000000 00001100 int number3; number3 = 1^((number2^(number1 << 5)) & 15); number3 = number3 >> 2; //Assume that the MSB shifted in is 0; printf("%d\n", number3);</pre>
<p>(7) [10pt]</p> <pre>#include <iostream> using std::cout; using std::endl; int scmp (char *s1, char *s2) { while (*s1 != '\0' && *s2 != '\0') { if (s1[0] > s2[0]) return 1; else if (s1[0] < s2[0]) return -1; else { s1++; s2++; } } // end while if (*s1 == *s2) return 0; else if (*s1 == '\0') return -1; else return 1; }</pre>	<pre>int main () { int i, size = 4; char *hold, *suit[4] = {"Hearts", "Diamonds", "Clubs", "Spades"}; for (int pass = 0; pass < size - 1; pass++) { for (i=0; i < size - 1; i++) if (scmp(suit[i], suit[i+1]) > 0) { hold = suit[i]; suit[i] = suit[i+1]; suit[i+1] = hold; } // end if cout << "In round " << pass << " : \n"; for (i=0; i < size; i++) cout << "s[" << i << "] = " << suit[i] << endl; } // end for pass return 0; }</pre>
<p>(8) [10pt]</p> <pre>#include <stdio.h> unsigned short encode(char *); int main () { unsigned int i; char cube[] = "10-01"; unsigned short output; output = encode(cube); printf("encoded output is: "); for (i=512; i > 0; i /= 2) { if (i & output) putchar('1'); else putchar('0'); } // end for i printf("\n"); return 0; }</pre>	<pre>unsigned short encode(char *input) { unsigned short temp, output = 0; int i, j; for (i=0; input[i] != NULL; i++) { switch(*(input+i)) { case '0': temp = 1; break; case '1': temp = 2; break; case '-': temp = 3; break; default: temp = 0; } // end switch for (j=0; j<i; j++) temp = temp << 2; output = output temp; } // end for i return output; }</pre>

- IV. [10pt] Write a C/C++ function, using do/while loop, to linearly interpolate 11 equal-space sampled points between (x1, y1) and (x2, y2).
- V. [10pt] For an engineer of digital circuit design, it is usual to view the circuit output in hexadecimal format. Please write a C/C++ function to translate a decimal number x10 to hexadecimal format, x16, for comparing the system simulation output with that of digital circuit designed.

注意：背面有試題

國立中央大學97學年度碩士班考試入學試題卷

所別：電機工程學系碩士班 電子組

科目：計算機概論

共 3 頁 第 3 頁

*請在試卷答案卷(卡)內作答

VI. [15pt] What is the output by the following program?

```
#include <iostream>
using std::cout;
using std::endl;

class CreateAndDestroy {
public:
    CreateAndDestroy(int); // constructor
    ~CreateAndDestroy(); // destructor
private:
    int data;
}; // end class CreateAndDestroy

CreateAndDestroy::CreateAndDestroy(int value)
{
    data = value;
    cout << "Object " << data << " constructor";
} // end CreateAndDestroy constructor

CreateAndDestroy::~~CreateAndDestroy()
{ cerr << "Object " << data << " destructor " << endl; }

void create(void);
CreateAndDestroy first(1);

int main()
{
    CreateAndDestroy third(2);
    create();
    static CreateAndDestroy second(3);
    CreateAndDestroy fourth(4);
    return 0;
} // end function main

// Function to create objects
void create(void)
{
    Static CreateAndDestroy fifth(5);
    CreateAndDestroy sixth(6);
} // end function create;
```

參考用

注：背面有試題
音