國立中央大學96學年度碩士班考試入學試題卷 共 2 頁 第 / 頁

# 所別:電機工程學系碩士班 丙組(一般生) 科目:信號與系統

#### **Question 1: (20%)**

Given a highpass filter for processing discrete-time input, its frequency response is

$$H_{hp}(e^{j\omega}) = \begin{cases} e^{-j\omega n_d}, & \omega_c < \omega < \pi \\ 0, & |\omega| < \omega_c \end{cases}, \text{ where } \omega_c \text{ is the ideal cutoff frequency.}$$

Please calculate its inverse Fourier transform, h,p[n].

#### **Question 2: (20%)**

Consider an LTI system, h[n], with frequency response

$$H(e^{j\omega}) = \frac{1 - e^{-j3\omega}}{1 + \frac{1}{2}e^{-j6\omega}}, -\pi < \omega < \pi$$

For a given input x[n] as

$$x[n] = \sin\left(\frac{\pi n}{3}\right)$$

Please determine the system output y[n], where y[n] is the convolution of x[n] and h[n].

#### **Question 3: (20%)**


For a causal sequence whose z-transform can be represented as

$$X(z) = \frac{(1+2z)(1+3z^{-1})}{(1-5z^{-1})}$$

Please determine its inverse z-transform, x[n].

### Question 4: (20%)

The system function H(z) of a causal linear time-invariant system has the pole-zero configuration shown in Fig. 4.1. It is also known that H(z) = 6 when z=1.



Answer the following questions:

- (a) (5%) Determine H(z).
- (b) (5%) Determine the impulse response h[n] of the system.
- (c) Determine the response of the system to the following input signals:
  - (i) (5%)  $x[n] = u[n] 0.5 \cdot u[n-1]$ .
  - (ii) (5%) the response x[n] obtained from sampling the continuous-time signal.

$$x(t) = 50 + 10\cos 20\pi t + 30\cos 40\pi t$$

at a sampling frequency  $\Omega s=2\pi(40)$  rad/s.



國立中央大學96學年度碩士班考試入學試題卷 # 2 頁 第 2 頁

### 所別:電機工程學系碩士班 丙組(一般生) 科目:信號與系統

## **Question 5: (20%)**

The following shows the block diagram of interpolator and decimator.




Figure 5.1

If we input a discrete-time signal  $x[n] = \frac{3\sin[(3/2)n]}{\pi n}$  to the interpolator-decimator system ( shown in Fig. 5.2) with L=2 and M=5, please determine the output y[n].




Figure 5.2